



**TYPE 1200P REGULATOR
FOR DOMESTIC TANK SUPPLY.**

34-410-0004 - Rev00

**INSTRUCTIONS FOR RE-SETTING
UNDER PRESSURE SHUT OFF (UPS0)**

The regulator system is of the latest most advanced design and incorporates many sophisticated features for your added security. In addition to the usual function of reducing the gas pressure to the precise and constant level required for your appliances, the system will automatically shut off the supply to your home in the unlikely event that the pressure should rise or fall to unacceptable levels.

Regulator adjustments are factory set and must not be altered. Qualified personnel may only adjust safety devices. However, there are two situations where the under pressure shut off could operate and may be re-set by the customer. These are as follows:

- The tank was allowed to become empty and has now been filled.
- The isolation valve on the tank has been turned off. (Ask your installer to identify this valve.)

YOU WILL BE AWARE IF EITHER OF THESE TWO CONDITIONS HAS OCCURRED.

If the supply has cut off for any reason, then contact your authorised service agent or supplier.

IF THE REGULATOR IS TO BE RE-SET, FIRST ENSURE THAT:

- All gas appliances are turned OFF.
- The isolation valve on the tank is fully open, turn anti-clockwise to open.

RESETTING PROCEDURE

TO RESET THE UNDER PRESSURE SHUT OFF (UPS0)

- Remove the black cover cap on the regulator.
- Grip the spindle firmly and pull do not push. You should be able to both hear and feel if the regulator has reset.
- Release the spindle gently and replace the black cover cap.
- Relight any permanent pilots and check that all appliances will light to ensure that the gas supply has been re-established.
- If the gas supply does not re-establish itself then check that all appliances are turned off and then repeat the reset procedure as detailed above.

If after two attempts the gas supply has not been re-established or you have any doubts of difficulty, contact the authorised service agent or gas supplier immediately.

IMPORTANT: This card should be retained by the consumer.